

Your PV Unit lets you set up a secret memory area that keeps your data safe and secure under a password you specify. After you enter the secret memory area, you can use the Scheduler, Contacts, Memo, and Expense Manager modes to store data.

Important!

- You can have only one secret memory area at any one time.
- All secret data for all modes is stored in the same secret memory area, regardless of what mode you were in when you created the secret memory area.
- Make sure you do not forget your password! There is no way to look up a password if you forget it. You will have to reset the PV Unit and clear all its memory contents in order to clear a forgotten password and create a new secret memory area.

Creating a New Secret Memory Area	106
To create a new secret memory area	106
Using the Secret Memory Area	107
To enter an existing secret memory area	107
To exit the secret memory area	107
To change your password	108
To transfer data from the open memory area to the secret memory area	108
To transfer data from the secret memory area to the open memory area	110

■ Creating a New Secret Memory Area

Use the following procedure to create a new secret memory area. Note that this operation can be performed only if there is no secret memory area already in memory.

To create a new secret memory area

1. Tap the **Menu** icon to display the Mode Menu, and then tap **Secret**.




2. Input up to 12 characters for the password you want to use.
 3. Tap **Set** to register your password and create a secret memory area.
 4. In response to the confirmation message that appears, tap **Yes**.
- Registering a password creates and immediately enters the secret memory area, which is indicated by the **Menu** icon.

Using the Secret Memory Area

The following describes the operations you can perform after you create a secret memory area.

To enter an existing secret memory area

1. Tap the **Menu** icon to display the Mode Menu, and then tap **Secret**.



2. Input the correct password, and then tap **Set**.
 - If the password is correct, the PV Unit enters the secret memory area.
 - Once you enter the secret memory area, you can move between it and the open (non-secret) memory area without having to input the password again until you turn power off and then back on again.

To exit the secret memory area

1. While in the secret memory area, tap the **Menu** icon to display the Mode Menu.
2. Tap **Secret** to exit the secret memory area and return to the open memory area.

To change your password

1. While in the secret memory area, tap the **Menu** icon to display the Mode Menu.
2. Tap the **Menu Bar** icon to display the menu bar, and then tap **Edit – Password edit**.




3. Input up to 12 characters for the new password you want to use.
4. Tap **Set** to register the new password.
5. In response to the confirmation message that appears, tap **Yes**.

To transfer data from the open memory area to the secret memory area

1. Enter the mode that contains the data you want to transfer to the secret memory area.
2. Select the data item you want to transfer.
 - You can select a data item (record) by highlighting it on a list screen, 1-Month Calendar screen, etc. or by displaying the data item's data screen.

3. Tap the **Menu Bar** icon to display the menu bar, and then tap **Edit – To secret area**.



4. Input the correct password and then tap **Set**.
 - You do not need to input the password if you have entered the secret memory area since you last turned on power.



5. Tap **Yes** to transfer the data.

To transfer data from the secret memory area to the open memory area

1. Enter the secret memory area.
2. Enter the mode that contains the data you want to transfer to the open memory area.
3. Select the data item you want to transfer.
 - You can select a data item (record) by highlighting it on a list screen, 1-Month Calendar screen, etc. or by displaying the data item's data screen.
4. Tap the **Menu Bar** icon to display the menu bar, and then tap **Edit – To open area**.



5. Tap **Yes** to transfer the data.